



## OVERVIEW

The Axxess Wireless Motion Sensor supports all motion dependent functions, including lighting, security, occupancy detection and energy management.

Upon detecting people moving in a space, it communicates that event wirelessly on a programmed schedule. It also measures temperature and light.

Utilizing a ball mount, the Wireless Motion Sensor is able to be adjusted to whatever direction you wish and enables quick removal.

The Wireless Motion Sensor can be combined with our Wireless Contact Switch to reliably determine occupancy status of a room. This is vital information for a variety of systems, including energy management, helping our environment while improving your bottom line.

Fully compatible with Control4.



# Motion Sensor

MS-C4ZB-R2

## USES

- Energy management
- Security systems
- Automatic lights
- Home & office automation

## WIRELESS

ZigBee PRO (802.15.4)  
Drivers downloadable

## COMPLIANCE/APPROVALS

FCC Part 15 | CE

## LIGHT SENSOR

Detects levels from light to dark

## POWER & BATTERY

- 2 - 1.5V AA alkaline/lithium batteries
- Low battery notification
- Over two year battery life

## MOTION SENSOR

- PIR motion sensor (dual element ambient effect reduction)
- Viewing Angle: 90° H, 30° V
- Effective range: 30'

## TEMPERATURE SENSOR

Accurate to +/- 1°C Operating range of -40°C to 70°C

## DIMENSIONS

W 2.3" x H 3.03" x D 0.5"  
W 5.84cm x H 7.7cm x D 1.27cm

## COLORS

White | Black

## DRIVERS

Download from  
[www.axxind.com/dealers/drivers](http://www.axxind.com/dealers/drivers)

## HOW TO ORDER

In US: [blackwiredesigns.com](http://blackwiredesigns.com)  
Outside US: [axxind.com/dealers](http://axxind.com/dealers)

## WHAT'S IN THE BOX

